TITLE OF THE INVENTION

CHARGED-PARTICLE BEAM EXPOSURE APPARATUS,

CHARGED-PARTICLE BEAM EXPOSURE METHOD,

CONTROL DATA DETERMINATION METHOD, AND

5          DEVICE MANUFACTURING METHOD USING THIS METHOD


FIELD OF THE INVENTION

         The present invention relates to a

charged-particle beam exposure apparatus, an exposure

10    method therefor, and a device manufacturing method

using this method or the like and, more particularly,

to a charged-particle beam exposure apparatus capable

of rapidly, properly performing proximity effect

correction in exposing a substrate to a charged

15    particle beam with a pattern, an exposure method

therefor, and a device manufacturing method using

this method or the like.


BACKGROUND OF THE INVENTION

20         Recently, an electron beam drawing apparatus is

used to draw a fine pattern on a sample such as a

semiconductor wafer or mask substrate.  This

apparatus suffers the influence of a so-called

proximity effect in which a pattern becomes thick or

25    thin owing to backward scattering electrons.

         One of effective methods of correcting the

- 1 -

proximity effect is a dosage correction method. As
the method of determining the optimal dosage, there
are adopted method (a) using a matrix (M. Parikhh, J.
App. Phys. 19, p. 4371, p. 4378, p. 4383 (1979)), and
method (b) using a simple approximate solution
formula (e.g., J.M. Parkovich, Journal of Vacuum
Science & Technology B4, p. 159 (1986)).

According to method (a), the relationship
between the dosage and the sensitivity at each
position is expressed by a matrix, and the inverse
matrix of this matrix is calculated to obtain an
optimal dosage at each position. The advantage of
this method is that an accurate optimal dosage can be
obtained by sufficiently decreasing the size of a
figure for which a dosage is set. The disadvantage
is a long calculation time. This method requires
several hundred to several thousand hours to correct
the proximity effect for all direct writing LSI chips.

According to method (b), an approximate value
D' of an optimal dosage is calculated by, e.g., the
following formulae (1) and (2):

$$D' = C/(1/2 + \eta U) \qquad \qquad \ldots (1)$$

$$U = (1/\pi) \int \exp\{-(x-x')^2 - (y-y')^2\}dx'dy' \quad \ldots (2)$$

where C is a constant, and $\eta$ is the ratio of a
resist sensitivity by forward scattering of an

electron beam to that by backward scattering.
Letting (x,y) be a dosage evaluation point, the
integral range of the parameter U is a rectangle
present within a circle having a radius about two or
5    three times the backward scattering radius using
(x,y) as the center, or a rectangle overlapping even
part of the circle.  However, even the use of the
approximate solution formulae requires several hours
to correct the proximity effect for all direct
10   writing LSI chips.

In this manner, the conventional methods
require at least several hours for a proximity effect
correction calculation time.  On the other hand, $\eta$,
the backward scattering radius, and the like as
15   parameters of proximity effect correction calculation
change depending on a resist applied to a target
wafer, the film material of a wafer surface, or the
like, so that parameters ($\eta$, backward scattering
radius, and the like) for achieving an optimal
20   proximity effect must be obtained.  For this purpose,
the step of changing parameters to recalculate
proximity effect correction, and the step of actually
exposing and evacuating a wafer using the
recalculated proximity effect correction are repeated.
25   This occupies an electron beam drawing apparatus for
several ten hours in order to only determine

parameters, which decreases the availability of the electron beam drawing apparatus.

## SUMMARY OF THE INVENTION

5     The present invention has been proposed to solve the conventional problems, and has as its object to provide a charged-particle beam exposure apparatus which can select a proper one of a plurality of pieces of correction exposure

10   information in accordance with the conditions of a surface to be exposed, thereby rapidly performing proper proximity effect correction, and an exposure method therefor.

    According to the first aspect of the present

15   invention, a charged-particle beam exposure apparatus for exposing a member to be exposed to a charged particle beam with a pattern comprises

    storage means for storing a plurality of data for controlling a dosage of the charged particle beam

20   in accordance with an irradiation position of the charged particle beam on the member to be exposed,

    selection means for selecting any one of the plurality of data stored in the storage means, and

    exposure means for controlling the dosage of

25   the charged particle beam for each irradiation position on the basis of the data selected by the

- 4 -

selection means, thereby exposing the member to be exposed with the pattern.

In the charged-particle beam exposure apparatus according to the first aspect of the present invention, for example, the control data preferably includes correction data for correcting influence of a proximity effect on reference dose data.

According to the second aspect of the present invention, a charged-particle beam exposure apparatus for exposing a member to be exposed to a charged particle beam with a pattern comprises

first storage means for storing reference dose data of the charged particle beam in accordance with an irradiation position of the charged particle beam on the member to be exposed,

second storage means for storing a plurality of control data for performing proximity effect correction for respective irradiation positions with respect to the reference dose data,

selection means for selecting one of the plurality of control data stored in the second storage means, and

exposure means for performing proximity effect correction for the reference dose data on the basis of the control data selected by the selection means, thereby exposing the member to be exposed with the

- 5 -

pattern.

In the charged-particle beam exposure apparatus according to the second aspect of the present invention, for example, the reference dose data preferably includes data for defining bitmap data determined depending on a pattern to be exposed, or data for defining bitmap data and an irradiation time ratio.

In the charged-particle beam exposure apparatus according to the second aspect of the present invention, for example, the control data preferably includes data which does not depend on a pattern to be exposed but depends on a condition of the member to be exposed.

In the charged-particle beam exposure apparatus according to the second aspect of the present invention, for example, the condition is preferably determined using as a parameter at least one of an underlayer condition of the member to be exposed, a resist material, and a backward scattering radius.

According to the third aspect of the present invention, a control data determination method comprises

the step of generating reference dose data of a charged particle beam for exposing a member to be exposed with a reference pattern,

- 6 -

the generation step of generating a plurality of control data for respective irradiation positions in accordance with conditions of the member to be exposed,

5      the storage step of storing in a memory the plurality of generated control data for the respective irradiation positions,

the selection step of selecting any one of the plurality of control data for the respective

10   irradiation positions that are stored in the memory,

the exposure step of performing proximity effect correction for the reference dose data on the basis of the selected control data, thereby exposing the member to be exposed with a pattern,

15   the determination step of evaluating the exposed pattern to determine whether the one selected control data is optimal data for controlling the reference dose data, and

the control data determination step of

20   determining optimal control data for controlling the reference dose data in accordance with a determination result,

wherein the selection step comprises selecting control data other than the one selected control data

25   until optimal control data is determined based on the determination result, and the determination step

comprises evaluating the exposed pattern based on the selected control data.

In the control data determination method according to the third aspect of the present invention, for example, whether the one selected control data is optimal data for controlling the reference dose data is preferably determined by comparing the exposed pattern with the reference pattern by a visual check.

In the control data determination method according to the third aspect of the present invention, for example, whether the one selected control data is optimal data for controlling the reference dose data is preferably determined by evaluation means for comparing the exposed pattern with the reference pattern.

In the control data determination method according to the third aspect of the present invention, for example, the reference dose data preferably includes data determined depending on a pattern to be exposed.

In the control data determination method according to the third aspect of the present invention, for example, the control data preferably includes data which does not depend on a pattern to be exposed but depends on a condition of the member

to be exposed.

In the control data determination method according to the third aspect of the present invention, for example, the condition is preferably determined using as a parameter at least one of an underlayer condition of the member to be exposed, a resist material, and a backward scattering radius.

According to the fourth aspect of the present invention, a charged-particle beam exposure method of exposing a member to be exposed to a charged particle beam with a pattern comprises

the step of generating a plurality of data for controlling a dosage of the charged particle beam in accordance with an irradiation position of the charged particle beam on the member to be exposed, and storing the data in a memory,

the selection step of selecting any one of the plurality of data stored in the memory, and

the exposure step of controlling the dosage of the charged particle beam for each irradiation position on the basis of the data selected in the selection step, thereby exposing the member to be exposed with the pattern.

In the charged-particle beam exposure method according to the fourth aspect of the present invention, for example, the control data preferably

includes correction data for correcting influence of a proximity effect on reference dose data.

According to the fifth aspect of the present invention, a charged-particle beam exposure method of exposing a member to be exposed to a charged particle beam with a pattern comprises

the step of generating reference dose data of the charged particle beam in accordance with an irradiation position of the charged particle beam on the member to be exposed, and storing the reference dose data in a first memory,

the step of generating a plurality of control data for performing proximity effect correction for respective irradiation positions with respect to the reference dose data, and storing the control data in a second memory,

the selection step of selecting one of the plurality of control data stored in the second memory, and

the exposure step of performing proximity effect correction for the reference dose data on the basis of the control data selected in the selection step, thereby exposing the member to be exposed with the pattern.

In the charged-particle beam exposure method according to the fifth aspect of the present

invention, for example, the reference dose data
preferably includes data determined depending on a
pattern to be exposed.

In the charged-particle beam exposure method
according to the fifth aspect of the present
invention, for example, the control data preferably
includes data which does not depend on a pattern to
be exposed but depends on a condition of the member
to be exposed.

In the charged-particle beam exposure method
according to the fifth aspect of the present
invention, for example, the condition is preferably
determined using as a parameter at least one of an
underlayer condition of the member to be exposed, a
resist material, and a backward scattering radius.

According to the sixth aspect of the present
invention, a device manufacturing method includes the
step of performing proximity effect correction for
each irradiation position of a charged particle beam
by the charged-particle beam exposure method
according to the fourth aspect, thereby exposing a
substrate with a pattern.

According to the seventh aspect of the present
invention, a device manufacturing method uses for
part of the manufacturing process a charged-particle
beam exposure apparatus for performing proximity

effect correction for a charged particle beam to expose a member to be exposed with a pattern, wherein the charged-particle beam exposure apparatus executes

the step of generating a plurality of control data for controlling reference dose data of the charged particle beam in accordance with an irradiation position of the charged particle beam on the member to be exposed, and storing the control data in a memory,

the selection step of selecting any one of the plurality of control data stored in the memory, and

the exposure step of controlling the reference dose data of the charged particle beam for each irradiation position on the basis of the control data selected in the selection step, thereby exposing the member to be exposed with the pattern.

According to the eighth aspect of the present invention, a device manufacturing method uses for part of the manufacturing process a charged-particle beam exposure apparatus for performing proximity effect correction for a charged particle beam to expose a member to be exposed with a pattern, wherein the charged-particle beam exposure apparatus executes

the step of generating reference dose data of the charged particle beam in accordance with an irradiation position of the charged particle beam on

the member to be exposed, and storing the reference

dose data in a first memory,

the step of generating a plurality of control

data for performing proximity effect correction for

5 respective irradiation positions with respect to the

reference dose data, and storing the control data in

a second memory,

the selection step of selecting one of the

plurality of control data stored in the second memory,

10 and

the exposure step of performing proximity

effect correction for the reference dose data on the

basis of the control data selected in the selection

step, thereby exposing the member to be exposed with

15 the pattern.

Other features and advantages of the present

invention will be apparent from the following

description taken in conjunction with the

accompanying drawings, in which like reference

20 characters designate the same or similar parts

throughout the figures thereof.


BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are

25 incorporated in and constitute a part of the

specification, illustrate embodiments of the

invention and, together with the description, serve to explain the principles of the invention.

Fig. 1 is a schematic view showing an electron beam exposure apparatus according to a preferred embodiment of the present invention;

Figs. 2A and 2B are views showing the detailed arrangement of a correction electron optical system;

Fig. 3 is a view showing one deflector formed on a blanker array;

Fig. 4 is a bottom view of the blanker array;

Fig. 5 is a view for explaining first and second electron optical system arrays;

Fig. 6 is a view for explaining the function of the correction electron optical system;

Fig. 7 is a block diagram showing the arrangement of the control system of the electron beam exposure apparatus shown in Fig. 1;

Fig. 8 is a view for explaining the exposure principle of the electron beam exposure apparatus shown in Fig. 1;

Fig. 9 is a block diagram showing the configuration of a system including the exposure apparatus;

Fig. 10 is a block diagram for explaining the arrangement of a BA control circuit;

Fig. 11 is a flow chart for explaining the flow

of evaluation processing for determining exposure

correction processing;

Fig. 12 is a table for explaining the

relationship between the drawing position and

5  correction exposure information;

Fig. 13 is a flow chart for explaining the

processes of a data controller and calculation unit;

Fig. 14 is a flow chart showing the

manufacturing flow of a microdevice (semiconductor

10  chip such as an IC or LSI, liquid crystal panel, CCD,

thin-film magnetic head, micromachine, or the like);

and

Fig. 15 is a flow chart showing the detailed

flow of the wafer process shown in Fig. 14.

15

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of the present invention

will now be described in detail in accordance with

the accompanying drawings.

20  The embodiments will explain an electron beam

exposure apparatus as an example of the

charged-particle beam exposure apparatus.  However,

the present invention is not limited to an electron

beam exposure apparatus, but can also be applied to,

25  e.g., an ion beam exposure apparatus.

Fig. 1 is a schematic view showing an electron

beam exposure apparatus according to a preferred embodiment of the present invention. Reference numeral 1 denotes an electron gun including a cathode 1a, grid 1b, and anode 1c. Electrons emitted by the cathode 1a form a crossover image as an electron source ES between the grid 1b and the anode 1c.

Electrons emitted by the electron source ES irradiate a correction electron optical system 3 via a condenser lens 2. The condenser lens 2 is comprised of, e.g., three aperture electrodes.

As shown in Fig. 2B, the correction electron optical system 3 is constituted by an aperture array AA, blanker array BA, correction electron optical system unit LAU, and stopper array SA sequentially arranged along an optical axis AX from the electron gun 1 side. Details of the correction electron optical system 3 will be described later.

The correction electron optical system 3 forms a plurality of intermediate images of the electron source ES, and each intermediate image is reduced and projected on a substrate 5 such as a wafer via a reduction electron optical system 4. Accordingly, a plurality of electron source images having the same shape are formed on the substrate 5. The correction electron optical system 3 forms these intermediate images so as to correct aberration generated upon

reducing and projecting the intermediate images on the substrate 5 via the reduction electron optical system 4.

The reduction electron optical system 4 is constituted by a symmetrical magnetic doublet made up of a first projection lens 41 and second projection lens 42, and a symmetrical magnetic doublet made up of a first projection lens 43 and second projection lens 44. Letting f1 be the focal length of the first projection lens 41 (43), and f2 be the focal length of the second projection lens 42 (44), the distance between the two lenses is f1+f2.

The object point on the optical axis AX is at the focal position of the first projection lens 41 (43), and the image point is at the focal point of the second projection lens 42 (44). This image is reduced to -f2/f1. Since the magnetic fields of the two lenses are determined to act in opposite directions in an exposure apparatus 100, Seidel aberrations and chromatic aberrations concerning rotation and magnification are theoretically canceled except for five aberrations, i.e., spherical aberration, isotropic astigmatism, isotropic coma, curvature of field, and on-axis chromatic aberration.

Reference numeral 6 denotes a deflector for deflecting a plurality of electron beams from the

correction electron optical system 3 and displacing a

plurality of electron source images on the substrate

5 by almost the same displacement amount in the X and

Y directions.  Although not shown, the deflector 6 is

5   comprised of a main deflector used when the scan

width is large, and a sub-deflector used when the

scan width is small.  The main deflector is an

electromagnetic deflector, whereas the sub-deflector

is an electrostatic deflector.

10      Reference numeral 7 denotes a dynamic focus

coil for correcting a shift in the focal position of

an electron source image caused by deflection

aberration generated upon operating the deflector 6;

and 8, a dynamic stigmatic coil for correcting

15  astigmatism among deflection aberrations generated by

deflection.

Reference numeral 9 denotes a $\theta$-Z stage which

supports the substrate 5 and is movable in the

optical axis AX (Z-axis) direction and the rotational

20  direction around the Z-axis.  A stage reference plate

10 is fixed to the $\theta$-Z stage 9.

Reference numeral 11 denotes an X-Y stage which

supports the $\theta$-Z stage and is movable in the X and Y

directions perpendicular to the optical axis AX

25  (Z-axis).

Reference numeral 12 denotes a

reflected-electron detector for detecting reflected
electrons generated upon irradiating a mark on the
stage reference plate 10 with an electron beam.

The arrangement of the correction electron
optical system 3 will be explained with reference to
Figs. 2A and 2B. As described above, the correction
electron optical system 3 is constituted by the
aperture array AA, blanker array BA, correction
electron optical system unit LAU, and stopper array
SA.

Fig. 2A is a view of the correction electron
optical system 3 when viewed from the electron gun 1,
and Fig. 2B is a sectional view taken along the line
A - A' in Fig. 2A.

As shown in Fig. 2A, the aperture array AA has
a plurality of apertures formed in a substrate, and
divides an electron beam from the condenser lens 2
into a plurality of electron beams.

The blanker array BA is obtained by forming on
one substrate a plurality of deflectors for
individually deflecting electron beams formed by the
aperture array AA. Fig. 3 is a view showing one
deflector formed in the blanker array BA. The
blanker array BA has a substrate 31 having a
plurality of apertures AP, blankers 32 each of which
is made up of a pair of electrodes via an aperture AP

and has a deflection function, and wiring lines W for individually turning on/off the blankers 32. Fig. 4 is a bottom view of the blanker array BA.

5 The correction electron optical system unit LAU is formed from first and second electron optical system arrays LA1 and LA2 as electron lens arrays each having a plurality of electron lenses two-dimensionally arrayed on the same plane.

10 Fig. 5 is a view for explaining the first electron optical system array LA1. The first electron optical system array LA1 has three, upper, intermediate, and lower electrode plates UE, CE, and LE on each of which a plurality of doughnut-like electrodes respectively corresponding to a plurality

15 of apertures are aligned. The three electrode plates are stacked via insulators.

The doughnut-like electrodes of the upper, intermediate, and lower electrode plates at the same X- and Y-coordinates form one electron lens

20 (so-called unipotential lens) UL. The doughnut-like electrode of the upper electrode plate of each electron lens UL is connected to an LAU control circuit 112 via a common wiring line W1, and the doughnut-like electrode of the lower electrode plate

25 of each electron lens UL is connected to the LAU control circuit 112 via a common wiring line W3. An

electron beam acceleration potential is applied between the doughnut-like electrodes of the upper and lower electrode plates. The doughnut-like electrode of the intermediate electrode plate of each electron

5   lens receives a proper potential from the LAU control circuit 112 via an individual wiring line W2. This structure can set electron optical power (focal length) of each electron lens to a desired value.

The second electron optical system array LA2

10  also has the same structure and function as those of the first electron optical system array LA1.

As shown in Fig. 2B, in the correction electron optical system unit LAU, the electron lenses of the first and second electron lens arrays LA1 and LA2 at

15  the same X- and Y- coordinates form one element electron optical system EL.

The aperture array AA is positioned on almost the front focal position side of the respective element electron optical systems EL. Each element

20  electron optical system EL, therefore, forms an intermediate image of the electron source ES at almost the rear focal position by each divided electron beam. To correct the curvature of field generated upon reducing and projecting an

25  intermediate image on the substrate 5 via the reduction electron optical system 4, a potential

applied to the doughnut-like electrode of the
intermediate electrode plate is adjusted for each
element electron optical system EL to adjust the
electron optical power of the electron lens, thereby

5    adjusting the intermediate image formation position.

Similar to the aperture array AA, the stopper
array SA has a plurality of apertures formed in a
substrate. An electron beam deflected by the blanker
array BA irradiates a portion outside an aperture of

10   the stopper array SA corresponding to the electron
beam, and is shielded by the substrate.

The function of the correction electron optical
system 3 will be explained with reference to Fig. 6.
Electrons emitted by the electron source ES pass

15   through the condenser lens 2 to form an almost
parallel electron beam. Almost the parallel electron
beam is divided into a plurality of electron beams by
the aperture array AA having a plurality of apertures.
The divided electron beams enter element electron

20   optical systems EL1 to EL3 to form intermediate
images img1 to img3 of the electron source ES at
almost the rear focal positions of the respective
element electron optical systems. These intermediate
images are projected via the reduction electron

25   optical system 4 on the substrate 5 serving as a
surface to be exposed.

To correct the curvature of field (shift between an actual imaging position and an ideal imaging position on the substrate 5 along the optical axis of the reduction electron optical system 4)

5 generated upon projecting a plurality of intermediate images on the surface to be exposed, the optical characteristics of a plurality of element electron optical systems are individually set to change the intermediate image formation position along the

10 optical axis for each element electron optical system.

Whether to irradiate the substrate 5 with each electron beam is individually controlled by blankers B1 to B3 of the blanker array BA and stoppers S1 to S3 of the stopper array SA. In Fig. 6, since the

15 blanker B3 is ON, an electron beam for forming the intermediate image img3 does not pass through the aperture S3 of the stopper array SA, and is shielded by the substrate of the stopper array SA.

Fig. 7 is a block diagram showing the

20 arrangement of the control system of the electron beam exposure apparatus 100 shown in Fig. 1. A BA control circuit 111 individually controls ON/OFF operation of the respective blankers of the blanker array BA. The detailed arrangement and function of

25 the BA control circuit 111 will be described later. The LAU control circuit 112 controls the focal length

of the electron lens EL forming the lens array unit
LAU. A D_STIG control circuit 113 controls the
dynamic stigmatic coil 8 to correct astigmatism of
the reduction electron optical system 4. A D_FOCUS

5    control circuit 114 controls the dynamic focus coil 7
to adjust the focus of the reduction electron optical
system 4. A deflection control circuit 115 controls
the deflector 6. An optical characteristic control
circuit 116 controls the optical characteristics

10   (magnification and distortion) of the reduction
electron optical system 4. A reflected-electron
detection circuit 117 calculates a reflected electron
amount on the basis of a signal from the
reflected-electron detector 12.

15       A stage driving control circuit 118 drives and
controls the $\theta$-Z stage 9, and drives and controls the
X-Y stage 11 in cooperation with a laser
interferometer LIM for detecting the position of the
X-Y stage 11.

20       A sub-controller 120 reads out exposure control
data from a memory 121 via an interface 122 to
control the control circuits 111 to 116 and 118 based
on the readout data, and controls the
reflected-electron detection circuit 117. A main

25   controller 123 integrally controls the whole electron
beam exposure apparatus 100.

The schematic operation of the electron beam exposure apparatus 100 shown in Fig. 1 will be described with reference to Fig. 7.

The sub-controller 120 reads out exposure control data from the memory 121, extracts, from the exposure control data, deflection control data (main deflector reference position, sub-deflector reference position, main deflection stage following data, and deflection control data) as control data for controlling the deflector 6, and provides the extracted data to the deflection control circuit 115. In addition, the sub-controller 120 extracts, from the exposure control data, blanker control data as control data for controlling each blanker of the blanker array BA, and data for correcting control of the blanker, and provides the extracted data to the BA control circuit 111. The provided data are respectively stored in a basic dose data memory 901 and proximity correction coefficient memories (902 to 905) of the BA control circuit 111.

The deflection control circuit 115 controls the deflector 6 based on the deflection control data to deflect a plurality of electron beams. At the same time, the BA control circuit 111 controls each blanker of the blanker array BA to turn on/off the blanker in accordance with a pattern to be drawn on

the substrate 5.  In scanning the substrate 5 with a
plurality of electron beams in order to draw a
pattern on the substrate 5, the X-Y stage 11 is
continuously driven in the Y direction, and a
5    plurality of electron beams are deflected by the
deflector 6 so as to follow movement of the X-Y stage
11.

       As shown in Fig. 8, each electron beam scans
and exposes a corresponding element exposure field
10   (EF) on the substrate 5.  This electron beam exposure
apparatus is designed such that element exposure
fields (EF) for respective electron beams are
two-dimensionally adjacent to each other, and a
subfield (SF) formed from a plurality of element
15   exposure fields (EF) is exposed at once.  In the
example shown in Fig. 8, one element exposure field
(EF) has a matrix of 8 x 8 elements.  Each element of
this matrix represents a field (position) where the
substrate 5 is irradiated with an electron beam
20   deflected by the deflector 6.  In other words, one
element exposure field (EF) having a matrix of 8 x 8
elements is scanned with one electron beam in a
direction indicated by an arrow in Fig. 8.

       After one subfield (SF1) is exposed, the
25   sub-controller 120 instructs the deflection control
circuit 115 to deflect a plurality of electron beams

by the deflector 6 in a direction (X direction)
perpendicular to the scan direction (Y direction) of
the X-Y stage 11 in scan/exposure so as to expose the
next subfield (SF2).

5      Aberration upon reducing and projecting each
electron beam via the reduction electron optical
system 4 also changes with switching of the subfield.
The sub-controller 120 instructs the LAU control
circuit 112, D_STIG control circuit 113, and D_FOCUS
10     control circuit 114 to adjust the lens array unit LAU,
dynamic stigmatic coil 8, and dynamic focus coil 7 so
as to correct the changed aberration.

       After the subfield is switched, a plurality of
electron beams execute exposure of corresponding
15     element exposure fields (EF) again to expose the
second subfield (SF2). As shown in Fig. 8, exposure
of subfields SF1 to SF6 is sequentially executed to
complete exposure of a main field (MF) formed from
the subfields SF1 to SF6 aligned in the direction (X
20     direction) perpendicular to the scan direction (Y
direction) of the X-Y stage 11 in scan/exposure.

       After exposure of the first main field (MF1)
shown in Fig. 8 is completed in this manner, the
sub-controller 120 instructs the deflection control
25     circuit 115 to sequentially deflect a plurality of
electron beams to main fields (MF2, MF3, MF4,...)

aligned in the scan direction (Y direction) of the
X-Y stage 11 and execute exposure. As a result, as
shown in Fig. 8, exposure of a stripe field (STRIPE1)
formed from the main fields (MF1, MF2, MF3, MF4,...)
5    is executed.

The sub-controller 120 instructs the stage
driving control circuit 118 to move the X-Y stage 11
by one step in the X direction, and executes exposure
of the next stripe field (STRIPE2).

10    Fig. 9 is a block diagram showing the
configuration of a system including the exposure
apparatus. This system is constituted by connecting
the electron beam exposure apparatus 100 shown in
Fig. 1 and an information processing apparatus 200

15   via a communication cable 210. The information
processing apparatus 200 acquires, e.g., exposure
pattern data from another information processing
apparatus via a communication cable 220, generates
compressed exposure control data suited for the

20   electron beam exposure apparatus 100 on the basis of
the exposure pattern data, and provides the generated
data to the electron beam exposure apparatus 100 via
the communication cable 210.

More specifically, the information processing

25   apparatus 200 acquires exposure pattern data from
another information processing apparatus via the

communication cable 220, and stores the exposure
pattern data in a storage 201. The exposure pattern
data may be acquired from a memory medium (e.g., a
magnetic tape or disk) which stores the data.

5       The information processing apparatus 200
generates in a control data generator 202 a plurality
of control data (containing, e.g., dot control data
or dose control data for controlling the blanker, and
deflection control data for controlling the
10     deflector) for controlling the electron beam exposure
apparatus 100 on the basis of the exposure pattern
data. The generated control data contain reference
dose data as basic exposure information.

        The reference dose data is information serving
15     as the base of drawing information depending on a
pattern to be exposed. The opening/closing state of
the blanker is controlled based on this information.
More specifically, the reference dose data includes
data (duty) for defining the structure of bitmap data
20     ("0" or "1"), or the bitmap structure and a blanker
opening/closing time (irradiation time ratio).

        Irradiation light emitted by the electron gun 1
has a predetermined irradiation intensity depending
on the light source, and irradiation energy can be
25     desirably controlled by the duty of the blanker. The
following "proximity effect correction" realizes an

irradiation (exposure) state most suited for a member
to be exposed by performing correction of
increasing/decreasing the duty defined by reference
dose data regardless of a drawing pattern in

5    consideration of various conditions of the member to
be exposed.

A correction exposure information generator 203
in the information processing apparatus 200 generates
correction exposure information for performing

10   proximity effect correction for each irradiation
position with respect to the reference dose data
generated by the control data generator 202.  The
correction exposure information is correction data
independent of an exposure pattern, and is generated

15   in consideration of the backward scattering radius,
resist material, difference in underlayer conditions,
and the like as parameters used when a surface is
exposed with a pattern.  The resist information,
underlayer information, and the like may refer to

20   resist & underlayer information 204 which is input
from an external terminal 300 and stored in the
information processing apparatus 200, or may refer to
information concerning an exposure pattern.  The duty
of the irradiation time is corrected for the

25   reference dose data having undergone proximity effect
correction.

Fig. 10 is a block diagram showing an
arrangement of the BA control circuit (Blanker Array
control circuit) 111 described with reference to
Fig. 7.  The blanker array control circuit 111

5      comprises the basic dose data memory 901 for storing
reference dose data serving as basic exposure
information, proximity correction coefficient memory
1 (902), proximity correction coefficient memory 2
(903),..., proximity correction coefficient memory m

10     (905) for storing pieces of correction exposure
information containing proximity effect correction
coefficients, a data controller 906 for executing
data control for performing proximity effect
correction for reference dose data serving as a base

15     in order to realize appropriate exposure for a member
to be exposed, a selector 907 for selecting one of
pieces of correction exposure information from the
proximity correction coefficient memories (902 to
905) in order to correct reference dose data, a

20     calculation unit 908 for calculating dose data having
undergone proximity effect correction for drawing a
pattern on a member to be exposed on the basis of the
selected correction exposure information and
reference dose data stored in the basic dose data

25     memory 901, a drawing dose data memory 909 for
temporarily storing an output of the calculation

result, and a driver 910 for driving the blanker on the basis of the corrected dose data.

The data controller 906 controls the calculation unit 908 based on a selection result from the selector 907, and executes data control for changing the duty of reference dose data.

Fig. 11 is a flow chart for explaining an evaluation flow concerning generation of data, and selection and determination of correction exposure information. In step S1101, reference dose data as basic exposure information is generated by the control data generator 202 of the information processing apparatus 200, and stored in the basic dose memory 901 of the BA control circuit 111.

In step S1102, pieces of correction exposure information containing proximity effect correction coefficients are generated by the correction exposure information generator 203 of the information processing apparatus 200, and stored in the proximity correction coefficient memories 902 to 905.

In step S1103, a pattern is drawn based on the reference dose data generated in step S1101.

In step S1104, whether proximity effect correction is necessary is checked from the drawn pattern. If NO in step S1104, evaluation ends (S1105). If YES in step S1104, the processing shifts

to step S1106 to select one of the pieces of correction exposure information stored in the proximity correction coefficient memories (902 to 905) (S1106). Then, a pattern is drawn based on dose data containing the selected correction exposure information (this will be called a "corrected pattern") (S1107).

The corrected pattern is evaluated in step S1108, and whether the correction exposure information selected in step S1106 is proper and whether the corrected pattern is optimal are checked in step S1109. If the selected correction exposure information is determined not to be proper, the processing returns to step S1106 to select another correction exposure information and repeat the same processes (S1107 and S1108).

If the corrected pattern is determined to be optimal in step S1109, the processing advances to step S1110 to determine the correction exposure information (S1110) and end evaluation (S1111).

During the processing of Fig. 11, processes concerning necessity/non-necessity of correction, selection of correction exposure information (steps S1104 and S1106), evaluation of a corrected pattern, and determination of optimum (steps S1108 and S1109) are desirably checked visually and selected by the

operator.  Alternatively, these processes can be done
by an evaluation apparatus for executing processes
corresponding to the respective steps (steps S1104,
S1106, S1108, and S1109).

5          Fig. 12 is a table showing the relationship
between the drawing position (Xn,Yn) and correction
exposure information B(n,m).  The drawing position is
coordinate components of a matrix forming an element
exposure field (EF) shown in Fig. 8, and is a unit
10    irradiated with a charged particle beam.  Reference
numeral 1201 denotes a drawing position by drawing
position coordinates expressed as a column matrix;
and 1202 and 1203, pieces of correction exposure
information generated under different conditions
15    which are in one-to-one correspondence with the
respective components of the drawing position.
Correction exposure information 1 (1202) and
correction exposure information m (1203) are
respectively stored in proximity correction
20    coefficient memory 1 (902) and proximity correction
coefficient memory m (905) in Fig. 10, and one of
them is selected by the selector 907.  Set correction
exposure information is not common to all the element
exposure fields (EF), and correction exposure
25    information is individually selected and set.

          Note that correction exposure information

contains data determined by the sequence of Fig. 11.

Fig. 13 is a flow chart for explaining the processes of the data controller 906 and calculation unit 908 (Fig. 10). Drawing of a corrected pattern having undergone proximity effect correction for each irradiation position will be explained in accordance with the flow chart.

The data controller 906 outputs to the calculation unit 908 reference dose data which has already been generated and stored in the basic dose data memory 901 (S1301). The data controller 906 outputs to the calculation unit 908 correction exposure information determined in accordance with the evaluation sequence of Fig. 11 (S1302).

The calculation unit 908 performs proximity effect correction for the reference dose data in accordance with the determined correction exposure information (S1303). This correction is to change the duty for controlling the opening/closing state of the blanker. For example, when the duty of the reference dose data is "1.0", correction of increasing the duty by 20% results in corrected dose data of "1.2", or correction of decreasing the duty by 20% results in corrected dose data of "0.8".

In step S1304, the calculation unit 908 checks whether proximity effect correction is completed for

the entire exposure field.  If NO in step S1304,

processing in step S1303 is continued; or if YES, the

calculation unit 908 outputs the corrected dose data

to the drawing dose data memory 909 (S1305).  Note

5    that the drawing dose data memory 909 functions as a

kind of buffer, and is not essential to the

arrangement of the embodiment according to the

present invention.  Hence, the calculation unit 908

may output the corrected dose data to the driver 910.

10   The driver 910 controls the opening/closing state of

the blanker in accordance with the corrected dose

data (S1306).

As described above, this embodiment can realize

exposure having rapidly undergone proximity effect

15   correction by selecting and determining appropriate

correction exposure information.

[Device Manufacturing Method]

An embodiment of a device manufacturing method

using the electron beam exposure apparatus 100

20   according to the above embodiment will be described.

Fig. 14 is a flow chart showing the

manufacturing flow of a microdevice (semiconductor

chip such as an IC or LSI, liquid crystal panel, CCD,

thin-film magnetic head, micromachine, or the like).

25   In step 1 (circuit design), a semiconductor device

circuit is designed.  In step 2 (creation of exposure

control data), the information processing apparatus
200 creates exposure control data of the exposure
apparatus based on the designed circuit pattern. In
step 3 (wafer manufacture), a wafer is manufactured
5   using a material such as silicon. In step 4 (wafer
process) called a pre-process, an actual circuit is
formed on the wafer by lithography using the electron
beam exposure apparatus 100 which has received the
exposure control data created in step 2. Step 5
10  (assembly) called a post-process is the step of
forming a semiconductor chip using the wafer
manufactured in step 4, and includes an assembly
process (dicing and bonding), packaging process (chip
encapsulation), and the like. In step 6 (inspection),
15  inspections such as the operation confirmation test
and durability test of the semiconductor device
manufactured in step 5 are conducted. After these
steps, the semiconductor device is completed and
shipped (step 7).
20      Fig. 15 is a flow chart showing the detailed
flow of the wafer process shown in Fig. 14. In step
11 (oxidation), the wafer surface is oxidized. In
step 12 (CVD), an insulating film is formed on the
wafer surface. In step 13 (electrode formation), an
25  electrode is formed on the wafer by vapor deposition.
In step 14 (ion implantation), ions are implanted in

the wafer. In step 15 (resist processing), a

photosensitive agent is applied to the wafer. In

step 16 (exposure), the electron beam exposure

apparatus 100 exposes the wafer to a circuit pattern.

5   In step 17 (developing), the exposed wafer is

developed. In step 18 (etching), the resist is

etched except for the developed resist image. In

step 19 (resist removal), an unnecessary resist after

etching is removed. These steps are repeated to form

10  multiple circuit patterns on the wafer.

The present invention can realize exposure

having rapidly undergone proximity effect correction

by selecting appropriate correction exposure

information.

15  As many apparently widely different embodiments

of the present invention can be made without

departing from the spirit and scope thereof, it is to

be understood that the invention is not limited to

the specific embodiments thereof except as defined in

20  the appended claims.